



WIRED CRESCENT FOOT SWITCH

Linemaster's wired digital foot switch comes in single, twin, and triple variations. The modern crescent design with built in handles provide the user with a foot pedal that is visually and ergonomically pleasing. Custom models are available to meet our customers needs. Only from Linemaster – American-made innovation at work. Call 860.974.1000 or visit our web site for more information.



LINEMASTER Switch Corporation
Tel (860) 974-1000

29 Plaine Hill Rd, P.O. Box 238
Woodstock, Connecticut
06281-0238 USA
Fax (800) 974-FOOT(3668)



WIRED CRESCENT FOOTSWITCH

FEATURES & BENEFITS:

- Switch Functions: Maximum of 5
- Up to 4 systems can be operating at the same time in the same room.
- Power consumption (Transmitter): stand-by- 100ua
- Standard Power Requirements (Receiver): 6VDC @ 200ma (other voltages optional)
- Receiver output: SPST realy, 0.5 amp contacts; SPDT relays optional
- Transmitter has EN60529 IP68 Degree of Protection
- Receiver has EN60529 IPX1 Degree of Protection
- No product calibration required - plug and go

CERTIFICATIONS:

Classified to IEC/UL 60601.1 Medical electrical equipment by Underwriter's Laboratories, Inc with respect to fire, shock, and mechanical hazards in accordance with IEC/UL 60601.1

Classified with respect to electric shock, fire, mechanical, and other specified hazards only, in accordance with Can/CSA C22.2 No. 60601.1

Meets EMC Directive EN60601-1-2

OPTIONS (CONSULT FACTORY FOR DETAILS)

- Custom labeling available
- Silk screening available
- Custom switch colors available
- Protective Bag available for easy clean-up
- Mode change switch available



SINGLE SWITCH

SIZE (HxWxD): 2.38 x 8.09 x 8.93 In.

WEIGHT: 7.50 lbs. WITHOUT CORDSET



TWIN SWITCH

SIZE (HxWxD): 2.38 x 14.00 x 10.00 In.

WEIGHT: 5.50 lbs. WITHOUT CORDSET



TRIPLE SWITCH

SIZE (HxWxD): 2.38 x 20.50 x 11.00In.

WEIGHT: 3.70 lbs. WITHOUT CORDSET

