



WIRED LINEAR CRESCENT FOOT SWITCH

Linemaster's Wired Linear Crescent foot switch series features a housing that is watertight to IP68 standards. Not only is this switch aesthetic and ergonomic, it also provides a smooth linear output for the control that you need. This switch, available in single, twin and triple models, has the option of additional auxiliary push button switches which suits many different applications. The use of Hall Effect sensors guarantee high reliability, no mechanical interface, high linearity and best of all no "Dead Spots". Linemaster's Wired Linear foot switch will offer you the consistent and precise feel that you have been looking for. Only from Linemaster – American made innovation at work. Call 860-974-1000 or visit our web site for more information.



LINEMASTER Switch Corporation
Tel (860) 974-1000

29 Plaine Hill Rd, P.O. Box 238
Woodstock, Connecticut
06281-0238 USA
Fax (800) 974-FOOT(3668)



WIRED LINEAR CRESCENT FOOTSWITCH

FEATURES:

- Switch Functions: Maximum combinations up to 3 linears and 6 switches
- Average power consumption varies per customer requirements
- Input Voltage 5-15 VDC
- Other voltages optional
- Independent Linearity 1-2%
- Linear output impedance 200 ohm maximum. Digital Switch <1 ohm
- Uses Hall Effect Sensors: High reliability, No Mechanical interface, High linearity, No dead spots
- EN 60529 Degree of Protection IP68
- Submersible for easy cleaning
- Meets IEC 60601-1-2 EMC requirements



SINGLE SWITCH

SIZE (HxWxD): 2.38 x 8.09 x 8.93 In.

WEIGHT: 3.70 lbs.



TWIN SWITCH

SIZE (HxWxD): 2.38 x 14.00 x 10.00 In.

WEIGHT: 5.50 lbs.



TRIPLE SWITCH

SIZE (HxWxD): 2.38 x 20.50 x 11.00In.

WEIGHT: 7.50 lbs.